



PHYSICS

BOOKS - NCERT PHYSICS (HINGLISH)

COMMUNICATION SYSTEM

Communication System

1. Three waves A,B and C of frequencies 1600 kHz, 5 MHz and 60 MHz, respectively are to be transmitted from one place to another.Which of the following is the appropriate mode of communication?

A. A is transmitted via space wave while B and C are transmitted via sky wave

B. A is transmitted via ground wave, B via sky wave and C via space wave

C. B and C are transmitted via ground wave while A is transmitted via sky wave

D. B is transmitted via ground wave while A and C are transmitted via space wave

Answer: B

 [Watch Video Solution](#)

2. A $100m$ long antenna is mounted on a $500m$ tall building. The complex can become a transmission tower of waves with λ

A. $\sim 400m$

B. $\sim 25m$

C. $\sim 150m$

D. $\sim 2400m$

Answer: A

 [Watch Video Solution](#)

3. A $1KW$ signal is transmitted using a communication channel which provides attenuation at the rate of $-2dBperkm$. If the communication channel has a total length of $5km$, the power of the signal received is

$$\left[\text{gain in } dB = 10 \log \left(\frac{P_0}{P_i} \right) \right]$$

- A. 900 W
- B. 100 W
- C. 990 W
- D. 1010 W

Answer: B

 [Watch Video Solution](#)

4. A speech signal of $3kHz$ is used to modulate a carrier signal of frequency $1MHz$, using amplitude modulation. The frequencies of the

side bands will be

A. 1.003 MHz and 0.997 MHz

B. 3001 kHz and 2997 kHz

C. 1003 kHz and 1000 kHz

D. 1 MHz and 0.997 MHz

Answer: A



[Watch Video Solution](#)

5. A message signal of frequency ω_m is superposed on a carrier wave of frequency ω_c to get an amplitude modulated wave (AM). The frequency of the AM wave will be

A. ω_m

B. ω_c


C. $\frac{\omega_c + \omega_m}{2}$

D. $\frac{\omega_c - \omega_m}{2}$

Answer: B


 [Watch Video Solution](#)

6. Identify the semiconductor devices whose characteristics are given below , in the order (a) ,(b) ,(c) ,(d) :




(a)

(a)



(b)

(b)



(c)

(c)

(d) 

A. (i) and (iii)

B. only (iii)

C. (ii) and some regions of (iv)

D. All the devices can be used

Answer: C



Watch Video Solution

7. A male voice after modulation-transmission sounds like that of a female to the receiver. The problem is due to

- A. poor selection of modulation index (selected $0 < m < 1$)
- B. poor bandwidth selection of amplifiers
- C. poor selection of carrier frequency
- D. loss of energy in transmission.

Answer: B



Watch Video Solution

8. A basic communication system consists of (A) transmitter (B) information source (C) user of information (D) channel (E) receiver`

Choose the correct sequence in which these are arranged in a basic communication system.

A. ABCDE

B. BADEC

C. BDACE

D. BEADC

Answer: B



[Watch Video Solution](#)

9. Identify the mathematical expression for amplitude modulated wave:

A. $A_c \sin[\{\omega_c + k_1 V_m(t)\}t + \phi]$

B. $A_c \sin\{\omega_c t + \phi + k_2 V_m(t)\}$

C. $\{A_c + k_2 V_m(t)\} \sin(\omega_c t + \phi)$

D. $A_c V_m(t) \sin(\omega_c t + \phi)$

Answer: C



Watch Video Solution

10. An audio signal of 15 kHz frequency cannot be transmitted over long distance without modulation because.

A. the size of the required antenna would be at least 5 km which is not convenient

B. the audio signal can not be transmitted through sky waves

C. the size of the required antenna would be at least 20 km, which is not convenient

D. effective power transmitted would be very low, if the size of the antenna is less than 5 km

Answer: A::B::D



[Watch Video Solution](#)

11. Audio sine waves of 3 kHz frequency are used to amplitude modulate a carrier signal of 1.5 MHz. Which of the following statements are true?

- A. The side band frequencies are 1506 kHz and 1494 kHz
- B. The bandwidth required for amplitude modulation is 6kHz
- C. The bandwidth required for amplitude modulation is 3 MHz
- D. The side band frequencies are 1503 kHz and 1497 kHz

Answer: B::D



[Watch Video Solution](#)

12. A TV transmission tower has a height of 240 m. Signals broadcast from this tower will be received by LOS communication at a distance of

(assume the radius of earth to be $6.4 \times 10^6 m$)

A. 100 km

B. 24 km

C. 55 km





D. 50 km

Answer: B::C::D



Watch Video Solution

13. The frequency response curve (figure) for the filter circuit used for production of AM wave should be



A. (i) followed by (ii)

B. (ii) followed by (i)

C. (iii)

D. (iv)

Answer: A::B::C



Watch Video Solution

14. In amplitude modulation, the modulation index μ , is kept less than or equal to 1 because.

- A. $m > 1$, will result in interference between carrier frequency and message frequency, resulting into distortion
- B. $m > 1$, will result in overlapping of both side bands resulting into loss of information
- C. $m > 1$, will result in change in phase between carrier signal and message signal

D. $m > 1$, indicates amplitude of message signal greater than amplitude of carrier signal resulting into distortion

Answer: B::D

 [Watch Video Solution](#)

15. Which of the following would produce analog signals and which would produce digital signals?

- A. A vibrating tuning fork
- B. Musical sound due to a vibrating sitar string
- C. Light pulse
- D. Output of NAND gate

Answer:

 [Watch Video Solution](#)

16. Would sky waves be suitable for transmission of TV signals of 60 MHz frequency?

 [Watch Video Solution](#)

17. Two waves A and B of frequencies 2MHz and 3 MHz, respectively are beamed in the same direction for communication via sky wave. Which one of these is likely to travel longer distance in the ionosphere before suffering total internal reflection?

 [Watch Video Solution](#)

18. The maximum amplitude of an AM wave is found to be 15 V while its minimum amplitude is found to be 3 V. What is the modulation index?

 [Watch Video Solution](#)


19. Compute LC product of a tuned amplifier circuit required to generate a carrier *wave* of 1MHz for amplitude modulation

[▶ Watch Video Solution](#)

20. Why is an AM signal likely to be more noisy than a FM signal upon transmission through a channel?

[▶ Watch Video Solution](#)

21. Figure (EP) shows a communication system. What is the output power when input signals is of 1.01 mW ? [gain in $\text{dB} = 10 \log_{10}(P_o / P_t)$].



[▶ Watch Video Solution](#)

22. A TV transmission tower of antenna is at a height of 20 m. How much service area can it cover if the receiving antenna is (i) at ground level (ii) at a height of 25 m ? Calculate the percentage increase in area covered in case (ii) relative to case (i).

 [Watch Video Solution](#)

23. If the whole earth is to be connected by LOS communication using space waves (no restriction of antenna size or tower height), what is the minimum no of antennaas required ? Calculate the tower height of these antennas in terms of earth's radius?

 [Watch Video Solution](#)

24. The maximum frequency for reflection of sky waves from a certain layer of the ionosphere is found to be $f_{\max} = 9(N_{\max})^{1/2}$, Where N_{\max} is

the maximum electron density at that layer of the ionosphere. On a certain day it is observed that signals of frequencies higher than 5 MHz are not received by reflection from the F_1 layer of the ionosphere while signals of frequencies higher than 8 MHz are not received by reflection from the F_2 layer of the ionosphere. Estimate the maximum electron densities of the F_1 and F_2 layers on that day.



[Watch Video Solution](#)

25. On radiation (sending out) an AM modulated signal, the total radiated power is due to energy carried by ω_c , $\omega_c - \omega_m$ and $\omega_c + \omega_m$. Suggest ways to minimise cost of radiation without compromising on information.



[Watch Video Solution](#)

26. (i) The intensity of a light pulse travelling along a communication channel decreases exponentially with distance x according to the relation $I = I_0 e^{-\alpha x}$, where I_0 is the intensity at $x = 0$ and α is the attenuation constant.

Show that the intensity reduces by 75 percent after a distance of $\frac{\ln 4}{\alpha}$

(ii) Attenuation of a signal can be expressed in decibel (dB) according to the relation


$\text{dB} = 10 \log_{10}(I/I_0)$. What is the attenuation in dB/km for an optical fibre in which the intensity falls by 50 percent over a distance of 50 km?

 [Watch Video Solution](#)

27. A 50 MHz sky wave takes 4.04 ms to reach a receiver via re-transmission from a satellite 600 km above earth's surface. Assuming re-transmission time by satellite negligible, find the distance between source and receiver. If communication between the two was to be done by Line of sight (LOS) method, what should be the size of transmitting antenna ?

 [Watch Video Solution](#)

28. An amplitude modulated wave is as shown in figure. Calculate (i) the percentage modulation, (ii) peak carrier voltage and , (iii) peak value of information voltage.



[▶ Watch Video Solution](#)

29. (i) Draw the plot of amplitude versus ω for an amplitude modulated wave whose carrier wave (ω_c) is carrying two modulating signals, ω_1 and ω_2 ($\omega_2 > \omega_1$).

(ii) Is the plot symmetrical about ω_c ? Comment especially about plot in region $\omega < \omega_c$.

(iii) Extrapolate and predict the problems one can expect if more waves

are to be modulated.

(iv) Suggest solutions to the above problem. In the process can one understand another advantage of modulation in terms of bandwidth?



[Watch Video Solution](#)

30. An audio signal is modulated by a carrier wave of 20 MHz such that the bandwidth required for modulation is 3 kHz. Could this wave be demodulated by a diode detector which has the values of R and C as (i) $R = 1k\Omega, C = 0.01\mu F$ (ii) $R = 10k\Omega, C = 0.01\mu F$ (iii) $R = 10k\Omega, C = 1\mu F$.



[Watch Video Solution](#)